

TRU-SCAPES

LANDSCAPE LIGHTING

SMART LANDSCAPE LIGHTING CONTROL



**WIRELESS
TRANSFORMER**



MADE IN USA



WWW.TRU-SCAPES.COM

SPECIAL FEATURES

- 150 Watt and 300 Watt models available
- Smart bluetooth wireless landscape lighting transformer
- Free APP downloads for Apple® and Android™ phones and tablets
- Power meter feature displays the watts used, available, and percent of full capacity
- Multiple low-voltage 14 Vac output terminals for use with LED lighting
- Astronomical and time-of-day based programs
- Create and save new custom programs
- Dashboard to check status and manually control the lights
- Anodized Aluminum Enclosure
- Energy efficiency certified
 - Department of Energy (DOE)
 - California Energy Commission (CEC)
- UL/cUL 1838 listed and FCC Part 15 Class B
- Made in the USA



SPECIFICATIONS

150 Watt Model:

Max Output Power:	150 W
Max Output Current:	12.5 A
Output Voltage Rating:	14 Vac
Output Terminals:	2
Input Voltage Rating:	120 Vac
IP Rating:	IP 21
Exterior Construction:	Anodized Aluminum

300 Watt Model:

Max Output Power:	300 W
Max Output Current:	20.5 A
Output Voltage Rating:	14 Vac
Output Terminals:	3
Input Voltage Rating:	120 Vac
IP Rating:	IP 21
Exterior Construction:	Anodized Aluminum

WWW.TRU-SCAPES.COM